

TYPE NUMBER	MFR	APP	COMP	GBP MIN	SLEW RATE MIN	V <sub>S+</sub> MAX	V <sub>S-</sub> MAX	T <sub>OP</sub> MAX	A <sub>VOL</sub> MIN	V <sub>IO</sub> MAX	I <sub>B</sub> MAX	I <sub>IO</sub> MAX	P <sub>TOT</sub> MAX	I <sub>OUT</sub> MIN	V <sub>OUT</sub> MIN	V <sub>ICM</sub> MAX	V <sub>IDF</sub> MAX	dV <sub>IO</sub> /dT MAX	P <sub>O</sub> MAX	I <sub>O</sub> MAX	CM RR MIN	PS RR MIN	R <sub>IN</sub> MIN
SNS2770L	TGU	HSR	EXT	.5MHZ	1V/uS	+22V	-22V	125C	94dB	4MV	15NA	2NA	500MWF	6MA	12V	15V	30V		60MW	2MA	80dB	76dB	30M
SNS2771FA	TGU	HSR	INT	.5MHZ	1V/uS	+22V	-22V	125C	94dB	4MV	15NA	2NA	500MWF	6MA	12V	15V	30V		60MW	2MA	80dB	76dB	30M
SNS2771JA	TGU	HSR	INT	.5MHZ	1V/uS	+22V	-22V	125C	94dB	4MV	15NA	2NA	500MWF	6MA	12V	15V	30V		60MW	2MA	80dB	76dB	30M
SNS2771JP	TGU	HSR	INT	.5MHZ	1V/uS	+22V	-22V	125C	94dB	4MV	15NA	2NA	500MWF	6MA	12V	15V	30V		60MW	2MA	80dB	76dB	30M
SNS2771L	TGU	HSR	INT	.5MHZ	1V/uS	+22V	-22V	125C	94dB	4MV	15NA	2NA	500MWF	6MA	12V	15V	30V		60MW	2MA	80dB	76dB	30M
SNS2777FA	TGU	PIA	EXT		0.2V/uS	+22V	-22V	125C	94dB	2MV	25NA	3NA	500MWF	5MA	12V	15V	30V	15uV/C		4MA	80dB	80dB	2M
SNS2777JA	TGU	PIA	EXT		0.2V/uS	+22V	-22V	125C	94dB	2MV	25NA	3NA	500MWF	5MA	12V	15V	30V	15uV/C		4MA	80dB	80dB	2M
SNS2777JP	TGU	PIA	EXT		0.2V/uS	+22V	-22V	125C	94dB	2MV	25NA	3NA	500MWF	5MA	12V	15V	30V	15uV/C		4MA	80dB	80dB	2M
SNS2777L	TGU	PIA	EXT		0.2V/uS	+22V	-22V	125C	94dB	2MV	25NA	3NA	500MWF	5MA	12V	15V	30V	15uV/C		4MA	80dB	80dB	2M
SNS2810FA	TGU	CPR	EXT			+14V	-7V	125C	82dB	2MV	15UA	3UA	300MWF	5MA	1V	7V	5V	10uV/C	150MW	9MA	80dB		
SNS2810J	TGU	CPR	EXT			+14V	-7V	125C	82dB	2MV	15UA	3UA	300MWF	5MA	1V	7V	5V	10uV/C	150MW	9MA	80dB		
SNS2810JP	TGU	CPR	EXT			+14V	-7V	125C	82dB	2MV	15UA	3UA	300MWF	5MA	1V	7V	5V	10uV/C	150MW	9MA	80dB		
SNS2810L	TGU	CPR	EXT			+14V	-7V	125C	82dB	2MV	15UA	3UA	300MWF	5MA	1V	7V	5V	10uV/C	150MW	9MA	80dB		
SNS2811FA	TGU	DCP	EXT			+14V	-7V	125C	82dB	3.5MV	20UA	3UA	300MWF	5MA	1V	7V	5V	20uV/C	150MW	7MA	70dB		
SNS2811J	TGU	DCP	EXT			+14V	-7V	125C	82dB	3.5MV	20UA	3UA	300MWF	5MA	1V	7V	5V	20uV/C	150MW	7MA	70dB		
SNS2811L	TGU	DCP	EXT			+14V	-7V	125C	82dB	3.5MV	20UA	3UA	300MWF	5MA	1V	7V	5V	20uV/C	150MW	7MA	70dB		
SNS2820J	TGU	DCP	EXT			+14V	-7V	125C	82dB	2MV	15UA	3UA	300MWF	5MA	1V	7V	5V	10uV/C	150MW	9MA	80dB		
SN72L022L	TGU	DLP	INT	.3MHZ	0.2V/uS	+18V	-18V	70C	60dB	5MV	250NA	80NA	500MWF	1MA	10V	15V	30V		4MW	3MA	60dB	74dB	
SN72L022P	TGU	DLP	INT	.3MHZ	0.2V/uS	+18V	-18V	70C	60dB	5MV	250NA	80NA	500MWF	1MA	10V	15V	30V		4MW	3MA	60dB	74dB	
SN72L044JA	TGU	QLP	INT	.3MHZ	.15V/uS	+18V	-18V	70C	60dB	5MV	250NA	80NA	500MWF	1MA	10V	15V	30V		4MW	1MA	60dB	74dB	
SN72L044N	TGU	QLP	INT	.3MHZ	.15V/uS	+18V	-18V	70C	60dB	5MV	250NA	80NA	500MWF	1MA	10V	15V	30V		4MW	1MA	60dB	74dB	
SN7510FA	TGU	BDO	EXT	.1GHZ		+8V	-8V	70C	36dB	30MV	100UA	30UA			1V	5V			220MW		70dB		3K
SN7510L	TGU	BDO	EXT	.1GHZ		+8V	-8V	70C	36dB	30MV	100UA	30UA			1V	5V			220MW		70dB		3K
SN7510P	TGU	BDO	EXT	.1GHZ		+8V	-8V	70C	36dB	30MV	100UA	30UA			1V	5V			220MW		70dB		3K
SN7511FA	TGU	BDO	EXT	.50MHZ		+8V	-8V	70C	50dB	5MV	20UA	10UA	500MWF	1MA	.75V	6V	6V	10uV/C	300MW		52dB		2K
SN7511L	TGU	BDO	EXT	.50MHZ		+8V	-8V	70C	50dB	5MV	20UA	10UA	500MWF	1MA	.75V	6V	6V	10uV/C	300MW		52dB		2K
SN7511N	TGU	BDO	EXT	.50MHZ		+8V	-8V	70C	50dB	5MV	20UA	10UA	500MWF	1MA	.75V	6V	6V	10uV/C	300MW		52dB		2K
SN7512L	TGU	BDO	EXT	.2GHZ		+8V	-8V	70C	46dB	7MV	80UA	5UA	500MWF	2MA	1.5V	6V	5V			25MA	74dB	50dB	2K
SN7512N	TGU	BDO	EXT	.2GHZ		+8V	-8V	70C	46dB	7MV	80UA	5UA	500MWF	2MA	1.5V	6V	5V			25MA	74dB	50dB	2K
SN7514L	TGU	BDO	EXT	.2GHZ		+8V	-8V	70C	46dB	7MV	80UA	5UA	500MWF	2MA	1.5V	6V	5V			25MA	74dB	50dB	2K
SN7514P	TGU	BDO	EXT	.2GHZ		+8V	-8V	70C	46dB	7MV	80UA	3UA	500MWF	2MA	1.5V	6V	5V			25MA	74dB	50dB	2K
SN72301AFA	TGU	GPU	EXT			+18V	-18V	70C	88dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	500K
SN72301AJ	TGU	GPU	EXT			+18V	-18V	70C	88dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	500K
SN72301AL	TGU	GPU	EXT			+18V	-18V	70C	88dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	500K
SN72301AN	TGU	GPU	EXT			+18V	-18V	70C	88dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	500K
SN72301AP	TGU	GPU	EXT			+18V	-18V	70C	88dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	500K
SN72306FA	TGU	CPR	EXT			+15V	-15V	70C	84dB	5MV	25UA	5UA	600MWF	50MA	2.5V			20uV/C	163MW				
SN72306J	TGU	CPR	EXT			+15V	-15V	70C	84dB	5MV	25UA	5UA	600MWF	50MA	2.5V			20uV/C	163MW				
SN72306L	TGU	CPR	EXT			+15V	-15V	70C	84dB	5MV	25UA	5UA	600MWF	50MA	2.5V			20uV/C	163MW				
SN72306N	TGU	CPR	EXT			+15V	-15V	70C	84dB	5MV	25UA	5UA	600MWF	50MA	2.5V			20uV/C	163MW				
SN72306P	TGU	CPR	EXT			+15V	-15V	70C	84dB	5MV	25UA	5UA	600MWF	50MA	2.5V			20uV/C	163MW				
SN72307FA	TGU	GPK	INT			+18V	-18V	70C	84dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C			70dB	70dB	0.5M
SN72307JA	TGU	GPK	INT			+18V	-18V	70C	84dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C			70dB	70dB	0.5M
SN72307L	TGU	GPK	INT			+18V	-18V	70C	84dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C			70dB	70dB	0.5M
SN72307N	TGU	GPK	INT			+18V	-18V	70C	84dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C			70dB	70dB	0.5M
SN72307P	TGU	GPK	INT			+18V	-18V	70C	84dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C			70dB	70dB	0.5M
SN72308AFA	TGU	SBA	EXT			+18V	-18V	70C	98dB	0.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	5uV/C		6MA	96dB	96dB	10M
SN72308AJA	TGU	SBA	EXT			+18V	-18V	70C	98dB	0.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	5uV/C		6MA	96dB	96dB	10M
SN72308AL	TGU	SBA	EXT			+18V	-18V	70C	98dB	0.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	5uV/C		6MA	96dB	96dB	10M
SN72308AN	TGU	SBA	EXT			+18V	-18V	70C	98dB	0.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	5uV/C		6MA	96dB	96dB	10M
SN72308AP	TGU	SBA	EXT			+18V	-18V	70C	98dB	0.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	5uV/C		6MA	96dB	96dB	10M
SN72308FA	TGU	SBA	EXT			+18V	-18V	70C	88dB	7.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	30uV/C		6MA	80dB	80dB	10M
SN72308JA	TGU	SBA	EXT			+18V	-18V	70C	88dB	7.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	30uV/C		6MA	80dB	80dB	10M
SN72308L	TGU	SBA	EXT			+18V	-18V	70C	88dB	7.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	30uV/C		6MA	80dB	80dB	10M
SN72308N	TGU	SBA	EXT			+18V	-18V	70C	88dB	7.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	30uV/C		6MA	80dB	80dB	10M
SN72308P	TGU	SBA	EXT			+18V	-18V	70C	88dB	7.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	30uV/C		6MA	80dB	80dB	10M
SN72310FA	TGU	VFA	INT		15V/uS	+18V	-18V	70C	0dB	7.5MV	7NA		500MWF	1MA	10V	15V	15V	50uV/C		6MA	6MA	70dB	10G
SN72310JA	TGU	VFA	INT		15V/uS	+18V	-18V	70C	0dB	7.5MV	7NA		500MWF	1MA	10V	15V	15V	50uV/C		6MA	6MA	70dB	10G
SN72310L	TGU	VFA	INT		15V/uS	+18V	-18V	70C	0dB	7.5MV	7NA		500MWF	1MA	10V	15V	15V	50uV/C		6MA	6MA	70dB	10G
SN72310N	TGU	VFA	INT		15V/uS	+18V	-18V	70C	0dB	7.5MV	7NA		500MWF	1MA	10V	15V	15V	50uV/C		6MA	6MA	70dB	10G

For detailed explanations of column heading notations, see App. A.

Also for ready references the more important abbreviations used in the column headings are listed below:

**LEFT HAND PAGE**

APP = application

(codes at APP.E.)

CMRR = common mode rejection ratio

CMP = compensation (frequency)

$dV_{IO}/dT$  = input offset voltage temperature drift

GBP = gain bandwidth product

$I_B$  = input bias current

$I_{IN}$  = input bias offset current

$I_Q$  = quiescent supply current

MFR = manufacturer (codes at App.C.)

$P_Q$  = quiescent power consumer

PSRR = power supply rejection ratio

$V_{ICM}$  = common mode input voltage rating

$V_{IOF}$  = differential input voltage rating

$V_{IO}$  = input offset voltage

$V_S$  = dc supply voltage

**RIGHT HAND PAGE**

Lead out coding summary (details at APP.G.) for different cases (APP.F.)

A = gain adjust

B = bias adjust

C = case

E- = inverting input

E+ = non-inverting input

F,F\* = input frequency compensation

G = ground

J = high level input

K = output, open collector

L = output, open emitter

M = metal case

N = not connected

O = special terminal

RR\* = outputs

S = strobe

T,T\* = offset balance

V+ = +ve dc supply

V- = -ve dc supply

W = guard ring

X = blank position, no lead

++ = +ve supplementary dc supply

-- = -ve supplementary dc supply

$\phi,\phi^*$  = output frequency compensation

CASE (APP.F.)	LD 1	LD 2	LD 3	LD 4	LD 5	LD 6	LD 7	LD 8	LD 9	LD 10	LD 11	LD 12	LD 13	LD 14	LD 15	LD 16	EUROPE SUBSTITUTE	USA SUBSTITUTE	IS	TYPE NUMBER	
T05-8/1M	TF	E-	E+	V-M	T*	R	V+	$\phi$	.	.	.	.	.	.	.	.	.	.	HA2-2505	O	SN52770L
FLP-14/3C	N	T	N	E-	E+	N	V-	N	T*	R	V+	N	N	N	.	.	.	.	.	O	SN52771FA
DIL-14/1C	N	T	N	E-	E+	N	V-	N	T*	R	V+	N	N	N	.	.	.	.	.	O	SN52771JA
DIL-8/1C	T	E-	E+	V-	T*	R	V+	N	.	.	.	.	.	.	.	.	.	.	.	O	SN52771JP
T05-8/1M	T	E-	E+	V-M	T*	R	V+	N	.	.	.	.	.	.	.	.	.	.	.	O	SN52771L
FLP-10/3C	N	TF	E-	E+	V-	T*	R	V+	F*	.	.	.	.	.	.	.	.	.	.	O	SN52777FA
DIL-14/1C	N	N	TF	E-	E+	V-	N	N	T*	R	V+	F*	N	N	.	.	.	.	.	O	SN52777JA
DIL-8/1C	TF	E-	E+	V-	T*	R	V+	F*	.	.	.	.	.	.	.	.	.	.	.	O	SN52777JP
T05-8/1M	TF	E-	E+	V-M	T*	R	V+	F*	.	.	.	.	.	.	.	.	.	.	.	O	SN52777L
FLP-10/3C	G	E+	E-	N	V-	R	N	V+	N	N	.	.	.	.	.	.	.	.	.	O	SN52810FA
DIL-14/1C	N	G	E+	E-	N	V-	N	N	R	N	V+	N	N	N	.	.	.	.	.	O	SN52810J
DIL-8/1C	G	E+	E-	V-	N	N	R	V+	.	.	.	.	.	.	.	.	.	.	.	O	SN52810JP
T05-8/1M	G	E+	E-	V-M	N	N	R	V+	.	.	.	.	.	.	.	.	.	.	.	O	SN52810L
FLP-10/3C	E-1	E+1	V-	E+2	E-2	S2	R	V+	G	S1	.	.	.	.	.	.	.	.	.	O	SN52811FA
DIL-14/1C	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	.	.	.	O	SN52811J
T05-10/1M	G	S1	E-1	E+1	V-	E+2	E-2	S2	R	V+	.	.	.	.	.	.	.	.	.	O	SN52811L
DIL-14/1C	R1	N	V+1	N	E+2	E-2	V-2	R2	N	V+2	G	E+1	E-1	V-1	.	.	.	.	.	O	SN52820J
T05-8/1M	R1	E-1	E+1	V-	E+2	E-2	R2	V+	.	.	.	.	.	.	.	.	.	.	.	O	SN72L022L
DIL-8/1P	R1	E-1	E+1	V-	E+2	E-2	R2	V+	.	.	.	.	.	.	.	.	.	.	.	O	SN72L022P
DIL-16/1C	R1	E-1	E+1	V-	E+2	E-2	R2	V+	R3	E-3	E+3	V-	E+4	E-4	R4	V+*	.	.	.	O	SN72L044JA
DIL-16/1P	R1	E-1	E+1	V-	E+2	E-2	R2	V+	R3	E-3	E+3	V-	E+4	E-4	R4	V+*	.	.	.	O	SN72L044N
FLP-10/3C	E	N	V+	N	E*	R*	G	N	R	V-	.	.	.	.	.	.	.	.	.	O	SN5510FA
T05-8/1M	E	V+	E*	M	R*	G	R	V-	.	.	.	.	.	.	.	.	.	.	SN5510FA	O	SN7510FA
DIL-8/1P	E	V+	E*	N	R*	G	R	V-	.	.	.	.	.	.	.	.	.	.	SN5510JP	O	SN7510L
FLP-10/3C	F	E	V+	E*	F*	R*	B	G	V-	R	.	.	.	.	.	.	.	.	SN5511FA	O	SN7510P
T05-10/1M	F	E	V+	E*	F*	R*	B	G	V-	R	.	.	.	.	.	.	.	.	SN5511L	O	SN7511FA
DIL-14/1P	N	F	E	V+	E*	F*	N	N	R*	B	G	V-	R	N	.	.	.	.	SN5511N	O	SN7511L
T05-10/1M	T*	E	V+	E*	N	R*	G	R	V-M	T	.	.	.	.	.	.	.	.	SN5512L	O	SN7512L
DIL-14/1P	N	T*	E	V+	E*	N	N	N	R*	G	R	V-	T	N	.	.	.	.	SN5512N	O	SN7512N
T05-8/1M	E+	V+	E*	M	R*	G	R	V-	.	.	.	.	.	.	.	.	.	.	SN5514L	O	SN7514L
DIL-8/1P	E	V+	E*	N	R*	G	R	V-	.	.	.	.	.	.	.	.	.	.	SN5514P	O	SN7514P
FLP-14/3C	N	N	FT	E-	E+	V-	N	N	T*	R	V+	F*	N	N	.	.	.	.	UA301AD	O	SN72301AFA
DIL-14/1C	N	N	FT	E-	E+	V-	N	N	T*	R	V+	F*	N	N	.	.	.	.	SFC2301A	O	SN72301AJ
T05-8/1M	FT	E-	E+	V-M	T*	R	V+	F*	.	.	.	.	.	.	.	.	.	.	LM301AH	O	SN72301AL
DIL-14/1P	N	N	FT	E-	E+	V-	N	N	T*	R	V+	F*	N	N	.	.	.	.	UA301AD	O	SN72301AN
DIL-8/1P	FT	E-	E+	V-	T*	R	V+	F*	.	.	.	.	.	.	.	.	.	.	SFC2301ADC	O	SN72301AP
FLP-14/3C	N	G	E+	E-	N	V-	S1	S2	R	N	V+	N	N	N	.	.	.	.	LM206F	O	SN72306FA
DIL-14/1C	N	G	E+	E-	N	V-	S1	S2	R	N	V+	N	N	N	.	.	.	.	SN52106J	O	SN72306J
T05-8/1M	G	E+	E-	V-M	S1	S2	R	V+	.	.	.	.	.	.	.	.	.	.	LM306G	O	SN72306L
DIL-14/1P	N	G	E+	E-	N	V-	S1	S2	R	N	V+	N	N	N	.	.	.	.	SN52106N	O	SN72306N
DIL-8/1P	G	E+	E-	V-	S1	S2	R	V+	.	.	.	.	.	.	.	.	.	.	SN52106P	O	SN72306P
FLP-14/3C	N	N	N	E-	E+	V-	N	N	N	R	V+	N	N	N	.	.	.	.	SN52107FA	O	SN72307FA
DIL-14/1C	N	N	N	E-	E+	V-	N	N	N	R	V+	N	N	N	.	.	.	.	SN52107JA	O	SN72307JA
T05-8/1M	N	E-	E+	V-M	N	R	V+	N	.	.	.	.	.	.	.	.	.	.	SFC2307	O	SN72307L
DIL-14/1P	N	N	N	E-	E+	V-	N	N	N	R	V+	N	N	N	.	.	.	.	SN52107JA	O	SN72307N
DIL-8/1P	N	E-	E+	V-	N	R	V+	N	.	.	.	.	.	.	.	.	.	.	SFC2307DC	O	SN72307P
FLP-10/1C	N	N	E-	E+	N	V-	R	V+	F	F*	.	.	.	.	.	.	.	.	SN52108AFA	O	SN72308AFA
DIL-14/1C	N	F	N	E-	E+	N	V-	N	N	R	V+	F*	N	N	.	.	.	.	UA308AD	O	SN72308AJA
T05-8/1M	F	E-	E+	V-M	N	R	V+	F*	.	.	.	.	.	.	.	.	.	.	SFC2308A	O	SN72308AL
DIL-14/1P	N	F	N	E-	E+	N	V-	N	N	R	V+	F*	N	N	.	.	.	.	UA308AD	O	SN72308AN
DIL-8/1P	F	E-	E+	V-	N	R	V+	F*	.	.	.	.	.	.	.	.	.	.	SN52108AP	O	SN72308AP
FLP-10/1C	N	N	E-	E+	N	V-	R	V+	F	F*	.	.	.	.	.	.	.	.	SFC2208PT	O	SN72308FA
DIL-14/1C	N	F	N	E-	E+	N	V-	N	N	R	V+	F*	N	N	.	.	.	.	UA308D	O	SN72308JA
T05-8/1M	F	E-	E+	V-M	N	R	V+	F*	.	.	.	.	.	.	.	.	.	.	SFC2308	O	SN72308L
DIL-14/1P	N	F	N	E-	E+	N	V-	N	N	R	V+	F*	N	N	.	.	.	.	UA308D	O	SN72308N
DIL-8/1P	F	E-	E+	V-	N	R	V+	F*	.	.	.	.	.	.	.	.	.	.	SFC2308DC	O	SN72308P
FLP-14/3C	N	N	T	N	E+	V-	N	N	L	R	V+	T*	N	N	.	.	.	.	SN52110FA	O	SN72310FA
DIL-14/1C	N	N	T	N	E+	V-	N	N	L	R	V+	T*	N	N	.	.	.	.	SFC2310EC	O	SN72310JA
T05-8/1M	T	N	E+	V-	L	R	V+	T*	.	.	.	.	.	.	.	.	.	.	UA310C	O	SN72310L
DIL-14/1P	N	N	T	N	E+	V-	N	N	L	R	V+	T*	N	N	.	.	.	.	SFC2310EC	O	SN72310N

# Appendix A

# Explanatory notes to tabulations

The general layout plan of the information in the tables of this compendium should be immediately evident from the data tabulation explanatory chart set out overleaf.

Supporting Appendices with additional information are:

- App. B Glossary of *Opamp Terms*
- App. C Tabulation *Codes for Manufacturers*
- App. D IC Manufacturers' *House Numbers*
- App. E Tabulation *Codes for Applications*
- App. F *Case Outline and Leadout Diagrams*
- App. G Codes for *Leadout Connections*

Unit symbols used in the tables are:

- A = amperes
- C = °centigrade
- dB = decibels
- G = gigaohms (megohms  $\times 10^3$ )
- GHZ = gigahertz (megahertz  $\times 10^3$ )
- K = kilohms
- KHZ = kilohertz
- M = megohms
- MA = milliamperes, mA
- MAX = maximum
- MHZ = megahertz
- MIN = minimum
- MV = millivolts
- MWC = milliwatts, case at 25C
- MWF = milliwatts, free air at 25C
- MWH = milliwatts, heat sink, 25C
- NA = nanoamps (microamps  $\times 10^{-3}$ )
- NV = nanovolts (microvolts  $\times 10^{-3}$ )
- PA = picoamps (microamps  $\times 10^{-12}$ )
- R = ohms
- T = teraohms (megohms  $\times 10^6$ )
- V = volts
- WC = watts, case at 25C
- WF = watts, free air at 25C
- WH = watts, heatsink, 25C
- $\mu$ A = microamps
- $\mu$ S = microseconds
- $\mu$ V = microvolts
- $\mu$ W = microwatts
- $\mu$ WF = microwatts, free air at 25C

Where a unit symbol appears in the middle of a value, it indicates the position of the decimal point, e.g. 3K3 = 3.3K.

Appendix A

TYPE NUMBER	MFR	APP	CMP	GBP MIN	SLEW RATE MIN	V <sub>S+</sub> MAX	V <sub>S-</sub> MAX	T <sub>OP</sub> MAX	A <sub>VOL</sub> MIN	V <sub>IO</sub> MAX	I <sub>B</sub> MAX	I <sub>IO</sub> MAX	P <sub>TOT</sub> MAX	I <sub>OUT</sub> MIN	V <sub>OUT</sub> MIN	V <sub>ICM</sub> MAX	V <sub>IDF</sub> MAX	dV <sub>IO</sub> /dT MAX	P <sub>O</sub> MAX	I <sub>O</sub> MAX	CMRR MIN	PSRR MIN	R <sub>IN</sub> MIN
(EXAMPLE) LH0022CH	NAU	FET	INT	.3MHZ	1V/US	+22V	-22V	85C	97dB	6MV	25pA	5pA	500MWF	10MA	10V	15V	30V	15uV/C	85MW	3MA	70dB	70dB	0.1T
<p>TYPE No. NUMERO-ALPHABETIC LISTING</p> <p>MFR = MANUFACTURER CODED AS APP. C</p> <p>APP = APPLICATION CODED AS APP. E</p> <p>CMP = FREQUENCY COMPENSATION WITH INT = INTERNAL EXT = EXTERNAL</p> <p>GBP MIN = UNITY GAIN BANDWIDTH PRODUCT, MIN; IN KHZ, MHZ, or GHZ</p> <p>SLEW RATE, MIN. IN VOLTS PER MICROSECOND. V/μS</p> <p>V<sub>S+</sub> MAX = MAX. PERMISSIBLE +VE DC SUPPLY VOLTAGE IN VOLTS, V</p> <p>V<sub>S-</sub> MAX = MAX. PERMISSIBLE -VE DC SUPPLY VOLTAGE IN VOLTS, V</p> <p>T<sub>OP</sub> MAX = MAX. PERMISSIBLE OPERATIONAL AMBIENT TEMPERATURE IN °C.</p> <p>A<sub>VOL</sub> MIN = MIN. OPEN-LOOP VOLTAGE GAIN IN DB</p> <p>V<sub>IO</sub> MAX = MAX INPUT OFFSET VOLTAGE AT 25°C IN MV or μV.</p> <p>I<sub>B</sub> MAX = MAX. INPUT BIAS CURRENT AT 25°C IN MA, μA, nA or pA</p>	<p>I<sub>O</sub> MAX = MAX. QUIESCENT (NO SIGNAL, NO LOAD) CURRENT CONSUMPTION IN MA</p> <p>P<sub>O</sub> MAX = MAX. QUIESCENT (NO SIGNAL, NO LOAD) POWER CONSUMPTION IN MW</p> <p>dV<sub>IO</sub>/dT MAX = MAX. INPUT OFFSET VOLTAGE TEMPERATURE DRIFT IN μV/C OR MV/C</p> <p>V<sub>IDF</sub> MAX = MAX. PERMISSIBLE DIFFERENTIAL INPUT VOLTAGE IN V.</p> <p>V<sub>ICM</sub> MAX = MAX. PERMISSIBLE COMMON-MODE INPUT VOLTAGE IN VOLTS, V</p> <p>V<sub>OUT</sub> MIN = GUARANTEED MIN. OUTPUT VOLTAGE, PEAK VALUE, IN VOLTS, V</p> <p>I<sub>OUT</sub> MIN = GUARANTEED MINIMUM OUTPUT CURRENT, PEAK VALUE, IN MA OR μA.</p> <p>P<sub>TOT</sub> MAX = MAX. PERMISSIBLE POWER DISSIPATION IN W, mW, μW WITH F = FREE AIR 25°C, C = CASE 25°C, H = HEATSINK 25°C.</p> <p>I<sub>IO</sub> MAX = MAX. INPUT OFFSET CURRENT AT 25°C IN MA, μA, nA, OR pA</p>	<p>R<sub>IN</sub> MIN = MIN. IN-PUT RESISTANCE</p> <p>PSRR MIN = MIN. POWER SUPPLY REJECTION RATIO IN DB</p> <p>CMRR MIN = MIN. COMMON MODE REJECTION RATIO IN DB</p>																					
<p>[NOTE: FOR FURTHER EXPLANATION OF SPECIAL TERMS SEE APP. B]</p>	<p>* R<sub>IN</sub> EXPRESSED AS OHMS (R), KILOHMS (K), MEGOHMS (M), GIGAOHMS (G) OR TERAHMS (T)</p>																						

## Appendix A

### LEFT HAND PAGE

For detailed explanations of column heading notations, see App. A.

Also for ready references the more important abbreviations used in the column headings are listed below:

- APP = application  
(codes at APP.E.)
- CMRR = common mode rejection ratio
- CMP = compensation  
(frequency)
- $dV_{io}/dT$  = input offset voltage temperature drift
- GBP = gain bandwidth product
- $I_b$  = input bias current
- $I_{io}$  = input bias offset current
- $I_Q$  = quiescent supply current
- MFR = manufacturer  
(codes at App.C.)
- $P_Q$  = quiescent power consumer
- PSRR = power supply rejection ratio
- $V_{icm}$  = common mode input voltage rating
- $V_{idc}$  = differential input voltage rating
- $V_{io}$  = input offset voltage
- $V_S$  = dc supply voltage

### RIGHT HAND PAGE

Lead out coding summary (details at APP.G.) for different cases (APP.F.)

- A = gain adjust
- B = bias adjust
- C = case
- E- = inverting input
- E+ = non-inverting input
- F,F\* = input frequency compensation
- G = ground
- J = high level input
- K = output, open collector
- L = output, open emitter
- M = metal case
- N = not connected
- Q = special terminal
- R,R\* = outputs
- S = strobe
- T,T\* = offset balance
- V+ = +ve dc supply
- V- = -ve dc supply
- W = guard ring
- X = blank position, no lead
- + + = +ve supplementary dc supply
- - = -ve supplementary dc supply
- $\phi, \phi^*$  = output frequency compensation

CASE (APP. F.)	LD 1	LD 2	LD 3	LD 4	LD 5	LD 6	LD 7	LD 8	LD 9	LD 10	LD 11	LD 12	LD 13	LD 14	LD 15	LD 16	EUROPE SUBSTITUTION	USA SUBSTITUTION	ISS	TYPE NUMBER	
T05-8/1M	T	E-	E+	V-	T*	R	V+	N	.	.	.	.	.	.	.	.	.	.	LH0022H	0	LH0022CH

CASE = PACKAGE OF DIFFERENT TYPES CODED ACCORDING TO APP. F - FIRST NUMBER INDICATES NUMBER OF LEAD POSITIONS EG DIL-14 = 14 LEAD DUAL-IN-LINE PACKAGE

LD1, LD2, ETC = LEAD NUMBERS WITH CONNECTIONS ACCORDING TO PAGE FOOTNOTE OR APP. G.

EURO SUBSTITUTION = PROELECTRON STANDARD OR OTHER TYPE AVAILABLE IN EUROPE

TYPE No. REPEATED ON R.H. MARGIN

ISS = ISSUE NUMBER OF DATA ENTRY

USA SUBSTITUTION = SUGGESTED ALTERNATIVE AVAILABLE IN USA.

# Appendix C

## Tabulation Codes for Manufacturers

<b>ADU</b>	<b>Advanced Micro Devices Inc.,</b> 901 Thompson Pl., Sunnyvale, CA 94086, USA	<b>ITU</b>	DA14 5HT, UK <b>ITT Semiconductors</b> 74 Commerce Way, Woburn, MA, 01801, USA
<b>ANG</b>	<b>Analog Devices Ltd,</b> Central Ave., East Molesey, KT8 9BR, Surrey, UK	<b>MNG</b>	<b>Mitsubishi Shoji Kaisha Ltd,</b> Bow Bells House, Bread St., London, EC4, UK
<b>ANU</b>	<b>Analog Devices Inc.,</b> P.O. Box 280, Norwood, Mass., 02062	<b>MNJ</b>	<b>Mitsubishi Electric Corp.,</b> 2-12 Marunouchi, Chiyoda-ku, Tokyo, Japan
<b>BLG</b>	<b>Bell &amp; Howell Ltd,</b> Lennox Road, Basingstoke, Hants, UK	<b>MTG</b>	<b>Motorola Ltd</b> (Semiconductor Products Div.), York House, Empire Way, Wembley, Middlesex, HA9 0PR, UK
<b>BLU</b>	<b>Bell &amp; Howell</b> (Control Products Divison), 706 Bostwick Ave, Bridgeport, Conn. 06605, USA	<b>MTU</b>	<b>Motorola Semiconductor Products Inc.,</b> 5005 E. McDowell Road, Phoenix, AZ, 85008, USA
<b>BUG</b>	<b>Burr-Brown International Ltd,</b> 17 Exchange Rd, Watford, WQD1 7EB, Herts., UK	<b>MUG</b>	<b>Mullard Ltd,</b> Mullard House, Torrington Place, London, WC1E 7HD, UK
<b>BUU</b>	<b>Burr-Brown Research Corp.,</b> P.O. Box 11400, Tucson, AZ, 85734, USA	<b>NAG</b>	<b>National Semiconductor (UK) Ltd,</b> Harpur Centre, Bedford, MK40 3LF, UK
<b>CMG</b>	<b>Computing Techniques Ltd,</b> Brookers Rd, Billingshurst, Sussex, RH14 9RZ, UK	<b>NAU</b>	<b>National Semiconductor Corp.,</b> 2900 Semiconductor Drive, Santa Clara, CA, 95051, USA
<b>DAG</b>	<b>Datel UK Ltd,</b> Stephenson Close, Portway Ind. Estate, Andover, Hants, UK	<b>NIJ</b>	<b>Nippon Electric Co. Ltd,</b> 1753 Shimonumabe, Nakahara-ku, Kawasaki, Japan
<b>DAU</b>	<b>Datel Systems Inc.,</b> 1020 Turnpike St., Canton, MA 02021, USA	<b>OAU</b>	<b>Opamp Labs Inc.,</b> 1033 N. Sycamore Ave., Los Angeles, CA 90038, USA
<b>FAG</b>	<b>Fairchild Camera &amp; Instrument (UK) Ltd,</b> 230 High St., Potters Bar, Herts., UK	<b>OBS</b>	Obsolete – no longer commercially available.
<b>FAU</b>	<b>Fairchild Semiconductor</b> 464 Ellis St., Mountain View, CA 94042, USA	<b>OTU</b>	<b>Optical Electronics Inc.,</b> P.O. Box 11140, Tucson, AZ, 85734, USA
<b>FEG</b>	<b>Ferranti Ltd,</b> (Electronic Department), Gem Mill, Chadderton, Oldham, Lancs., OL9 8NP, UK	<b>PLG</b>	<b>Plessey Semiconductors,</b> Cheney Manor, Swindon, Wilts., SN2 2QW, UK
<b>FUJ</b>	<b>Fujitsu Ltd,</b> 1015 Kamikodanaka, Kawasaki, Japan	<b>PRG</b>	<b>Precision Monolithics</b> (Bourns Trimpot Ltd) 17/27 High St., Hounslow, Middlesex, UK
<b>HAG</b>	<b>Harris Semiconductor (Memec) Ltd,</b> The Firs, Whitchurch, Nr. Aylesbury, Bucks., HP22 4JU, UK	<b>PRU</b>	<b>Precision Monolithics (Bourns) Inc.,</b> 1500 Space Park Drive, Santa Clara, CA, 95050, USA
<b>HAU</b>	<b>Harris Semiconductor</b> P.O. Box 883, Melbourne, FL, 32901, USA	<b>RAG</b>	<b>Raytheon Semiconductor</b> The Pinnacles, Harlow, Essex, CM19 5BB, UK
<b>HIJ</b>	<b>Hitachi Ltd</b> (Semiconductor and IC Div.), 1450 Josuihonimachi, Kodaira City, Tokyo, Japan	<b>RAU</b>	<b>Raytheon Semiconductor,</b> 350 Ellis Street, Mountain View, CA, 94042, USA
<b>ING</b>	<b>Intersil Inc.,</b> 8 Tessa Rd, Richfield Trading Estate, Reading, Berks., UK	<b>RCG</b>	<b>RCA (Great Britain) Ltd,</b> Lincoln Way, Windmill Road, Sunbury-on- Thames, Middlesex, UK
<b>INU</b>	<b>Intersil Inc.,</b> 10900 N. Tantau Ave, Cupertino, CA, 95014, USA	<b>RCU</b>	<b>RCA Solid State Division</b> Route 202, Somerville, NJ, 08876, USA
<b>ITG</b>	<b>ITT Semiconductors</b> Maidstone Rd, Fooks Cray, Sidcup, Kent,	<b>SAJ</b>	<b>Sanken Electric Co. Ltd,</b> 1-22-8 Nishi-Ikebukuro, Toshima-Ku, Tokyo, Japan

Appendix C

<b>SGG</b>	<b>SGS-ATES (UK) Ltd,</b> Planar House, Walton Street, Aylesbury, Bucks., UK	<b>SPU</b>	<b>Sprague Electric Company</b> (Semiconductor Div.), 115 Northeast Cutoff, Worcester, MA, 01606, USA
<b>SGI</b>	<b>SGS-ATES Componenti Spa,</b> Via Olivetti, 2 Agrate Brianza, 20041, Milan, Italy	<b>TDG</b>	<b>Teledyne Semiconductor,</b> Heathrow House, Bath Road, Cranford, Hounslow, Middlesex, TW5 9QP, UK
<b>SHG</b>	<b>Shindengen Hyokuto Boeki Haisha Ltd,</b> St. Alphage House, Fore St., London, EC2Y 5DA, UK	<b>TDU</b>	<b>Teledyne (Amelco) Semiconductor,</b> 1300 Terra Bella Ave, Mountain View, CA, 94032, USA
<b>SHJ</b>	<b>Shindengen Electric Mfg Co., Ltd,</b> New Ohtemachi Bldng, 2-1, 2-chome, Ohtemachi, Chiyoda-ku, Tokyo, Japan	<b>TEB</b>	<b>Teledyne-Philbrick,</b> Heathrow House, Bath Road, Cranford, Hounslow, Middlesex, TW5 9QP, UK
<b>SIG</b>	<b>Siemens Ltd,</b> Great West Road, Brentford, Middlesex, TW8 9DG, UK	<b>TEU</b>	<b>Teledyne-Philbrick,</b> Allied Drive at Route 128, Dedham, MA, 02026, USA
<b>SIW</b>	<b>Siemens Aktiengesellschaft,</b> Richard-Strauss-Strasse 76, D-8000 Munchen 2, Postfach 202109, W. Germany	<b>TGG</b>	<b>Texas Instruments Ltd,</b> Manton Lane, Bedford, UK
<b>SJG</b>	<b>Signetics International Corporation</b> Yeoman House, 63 Croydon Rd, London, SE20, UK	<b>TGU</b>	<b>Texas Instruments Inc.</b> (Components Group), P.O. Box 5012, Dallas, Texas, 75222, USA
<b>SJU</b>	<b>Signetics Corp.,</b> 811 East Arques Ave, Sunnydale, CA. 94086, USA	<b>THF</b>	<b>Thomson-CSF (Sescosem),</b> 50 Rue Jean Pierre Timbaud, BP 120, 92403, Courbevoie, France
<b>SKU</b>	<b>Silicon General Inc.,</b> 7382 Bolsa Avenue, Westminster, CA, 92683, USA	<b>THG</b>	<b>Thomson-CSF (UK) Ltd,</b> Ringway House, Bell Rd, Daneshill, Basingstoke, Hants., RG24 0QG, UK.
<b>SLG</b>	<b>Siliconix Ltd,</b> 30A High St., Thatcham, Newbury, Berks., RG13 4JG, UK	<b>TKJ</b>	<b>Tokyo Sanyo Electric Co. Ltd</b> (Semiconductor Div.), Oizumachi, Oragun, Gumma, Japan
<b>SLU</b>	<b>Siliconix Incorporated,</b> 2201 Laurelwood Road, Santa Clara, CA, 95054, USA	<b>TOG</b>	<b>Toshiba (UK) Ltd,</b> Toshiba House, Great South West Rd, Feltham, Middlesex, UK
<b>SOJ</b>	<b>Sony Semiconductor Corp.,</b> 14-1, Asa hi-sho 4, Atsuigi-shi, Kanagawa-ken, 243, Japan	<b>TOJ</b>	<b>Toshiba (Tokyo Shibaura) Electric Co.,</b> 2-1, 5-chome, Ginza Chuo-ku, Tokyo, Japan
<b>SPG</b>	<b>Sprague Electric (UK) Ltd,</b> 159 High St., Yiewsley, W. Drayton, Middlesex, UB7 7RY, UK	<b>TRU</b>	<b>Transitron Electronic Corp.,</b> 168 Albion St., Wakefield, MA, 01881, USA
		<b>ZEU</b>	<b>Zeltex Inc.,</b> 940 Detroit Ave, Concord, CA, 94518, USA

# Appendix D

## IC Manufacturers'

### House Numbers

(General Note: Manufacturers often adopt their own 'in-house' serial numbering for their ICs. Listed below are the initial letters of numerical series used by different manufacturers.)

<b>AD</b>	Analog Devices	<b>OP</b>	Precision Monolithics
<b>ADO</b>	Analog Devices	<b>P</b>	Teledyne-Philbrick
<b>AM</b>	Advanced Micro Devices; Datel	<b>PF</b>	Teledyne-Philbrick
<b>AMD</b>	Advanced Micro Devices	<b>PG</b>	General Instruments (obs.)
<b>AMLM</b>	Advanced Micro Devices	<b>PP</b>	Teledyne-Philbrick
<b>AMSSS</b>	Advanced Micro Devices	<b>RA</b>	Radiation (now Harris)
<b>AMU</b>	Advanced Micro Devices	<b>RC</b>	Raytheon
<b>C</b>	Bell & Howell	<b>RL</b>	Raytheon
<b>CA</b>	RCA	<b>RM</b>	Raytheon
<b>CIA</b>	Teledyne-Philbrick	<b>RSN</b>	Raytheon
<b>CMP</b>	Precision Monolithics	<b>RV</b>	Raytheon
<b>CN</b>	Ferranti	<b>S</b>	Signetics
<b>DA</b>	Teledyne-Philbrick	<b>SA</b>	Teledyne-Philbrick
<b>EP</b>	Teledyne-Philbrick	<b>SE</b>	Signetics; Mullard
<b>ESL</b>	Teledyne-Philbrick	<b>SFC</b>	Thomson-CSF
<b>FSL</b>	Teledyne-Philbrick	<b>SG</b>	Silicon General
<b>FSS</b>	Ferranti	<b>SH</b>	Fairchild
<b>HA</b>	Harris	<b>SK</b>	RCA
<b>HEPC</b>	Motorola	<b>SL</b>	Plessey; Teledyne-Philbrick
<b>ICH</b>	Intersil	<b>SN</b>	Texas Instruments
<b>ICL</b>	Intersil	<b>SP</b>	Teledyne-Philbrick
<b>JM</b>	Fairchild	<b>SQ</b>	Teledyne-Philbrick
<b>JSF</b>	Thomson-CSF	<b>SSS</b>	Precision Monolithics
<b>L</b>	Analog Devices; SGS-ATES	<b>SU</b>	Signetics; Mullard
<b>LA</b>	Teledyne-Philbrick	<b>T</b>	Teledyne-Philbrick Transitron
<b>LF</b>	National Semiconductor	<b>TA</b>	AEG-Telefunken
<b>LH</b>	National Semiconductor	<b>TAA</b>	Proelectron Standard
<b>LM</b>	National Semiconductor	<b>TBA</b>	Proelectron Standard
<b>M</b>	Mitsubishi	<b>TBB</b>	Proelectron Standard
<b>MC</b>	Motorola Semiconductors	<b>TBC</b>	Proelectron Standard
<b>MCC</b>	Motorola Semiconductors	<b>TBE</b>	Proelectron Standard
<b>MCCF</b>	Motorola Semiconductors	<b>TCA</b>	Proelectron Standard
<b>MCE</b>	Motorola Semiconductors	<b>TDA</b>	Proelectron Standard
<b>MCH</b>	Motorola Semiconductors	<b>TDB</b>	Proelectron Standard
<b>MIC</b>	ITT Semiconductors	<b>TDC</b>	Proelectron Standard
<b>MLF</b>	Motorola; Teledyne-Philbrick	<b>TDE</b>	Proelectron Standard
<b>MLM</b>	Motorola Semiconductors	<b>TL</b>	AEG-Telefunken
<b>MLMC</b>	Motorola Semiconductors	<b>TOA</b>	Transitron
<b>MONO-OP</b>	Precision Monolithics	<b>TSC</b>	Transitron
<b>N</b>	Signetics; Mullard	<b>U</b>	Fairchild
<b>NC</b>	General Instruments (obs.)	<b>ULN</b>	Sprague
<b>NE</b>	Signetics; Mullard	<b>ULS</b>	Sprague
<b>NH</b>	National Semiconductor	<b>USL</b>	Teledyne-Philbrick
		<b>ZA</b>	Zeltex
		<b>ZEL</b>	Zeltex
		<b>ZLD</b>	Ferranti
		<b>ZN</b>	Ferranti
		<b>μA</b>	Fairchild



# Appendix E

## Tabulation Codes for Applications

<b>BDO</b>	Balanced differential-output amplifier	<b>PAA</b>	Parametric amplifier
<b>CDA</b>	Current-difference amplifier	<b>PIA</b>	Precision instrumentation amplifier
<b>CHP</b>	Chopper-stabilized amplifier	<b>PRA</b>	Programmable opamp
<b>CPR</b>	DC comparator	<b>QCD</b>	Quad current-difference amplifier
<b>DBD</b>	Dual balanced differential-output amplifier	<b>QCP</b>	Quad comparator
<b>DCP</b>	Dual Comparator	<b>QFE</b>	Quad fet-input opamp
<b>DFE</b>	Dual fet-input opamp	<b>Q GK</b>	Quad general-purpose, internally-compensated, opamp
<b>DGK</b>	Dual general purpose opamp	<b>QGU</b>	Quad general-purpose, uncompensated, opamp
<b>DGU</b>	Dual general-purpose uncompensated opamp	<b>QLQ</b>	Quad low-quiescent-power opamp
<b>DHS</b>	Dual high-slew-rate opamp	<b>QPI</b>	Quad precision instrumentation amplifier
<b>DLN</b>	Dual low-noise opamp	<b>QPR</b>	Quad programmable opamp
<b>DPI</b>	Dual precision instrumentation amplifier	<b>QSB</b>	Quad super-beta opamp
<b>DPR</b>	Dual programmable opamp	<b>SBA</b>	Super-beta opamp
<b>DSB</b>	Dual super-beta opamp	<b>TCP</b>	Triple comparator
<b>FET</b>	Fet-input opamp	<b>TFE</b>	Triple fet-input opamp
<b>GPK</b>	General-purpose, internally-compensated, opamp	<b>TGK</b>	Triple general-purpose, internally compensated, opamp
<b>GPU</b>	General-purpose, uncompensated, opamp	<b>TGU</b>	Triple general-purpose, uncompensated, opamp
<b>HCO</b>	High current output opamp	<b>TLN</b>	Triple low-noise opamp
<b>HIR</b>	High input resistance opamp	<b>TLP</b>	Triple low-quiescent-power opamp
<b>HPO</b>	High power output opamp	<b>TOT</b>	Triple operational transconductance amplifier
<b>HSR</b>	High slew rate opamp	<b>TPI</b>	Triple precision instrumentation amplifier
<b>HVO</b>	High voltage output opamp	<b>TPR</b>	Triple programmable opamp
<b>LBC</b>	Low input bias current opamp	<b>TSB</b>	Triple super-beta opamp
<b>LCD</b>	Low input offset current drift opamp	<b>VFA</b>	Voltage-follower amplifier
<b>LNA</b>	Low noise opamp	<b>WBA</b>	Wide-band opamp
<b>LOC</b>	Low input offset current opamp	<b>XHG</b>	Extra-high-gain opamp
<b>LOV</b>	Low input offset voltage opamp	<b>XLP</b>	Extra-low quiescent power opamp
<b>LQP</b>	Low quiescent power opamp	<b>XSR</b>	Extra-high slew rate opamp
<b>LVD</b>	Low input offset voltage drift opamp	<b>XWB</b>	Extra-wide-band opamp
<b>MWB</b>	Medium-wideband opamp		
<b>OTA</b>	Operational transconductance amplifier		

# Appendix G

## Codes for Leadout Connections

### *I: Connection Codes in Serial Order*

A	= Gain adjust, 1
A*	= Gain adjust, 2
B	= Bias adjust or set
C	= Case, package, screen
E+	= Input, non-inverting, low-level
E-	= Input, inverting, low-level
F	= Input frequency compensation, 1
F*	= Input frequency compensation, 2
G	= Ground, common, earth, zero volts
J+	= Input, non-inverting, high-level
J-	= Input, inverting, high-level
K	= Output, open collector
L	= Output, open emitter
M	= Metal casing
N	= Not connected, i.e. isolated lead
Q	= Special terminal (consult manufacturer's data)
R	= Output, 1
R*	= Output, 2
S	= Strobe
T	= Offset balance, trim or null, 1
T*	= Offset balance, trim or null, 2
V+	= +ve dc supply
V-	= -ve dc supply
W	= Guard ring
X	= Blank position, lead omitted
++	= +ve supplementary dc supply
--	= -ve supplementary dc supply
φ	= Output frequency compensation, 1
φ*	= Output frequency compensation, 2

### *II: Lead Assignments in Alphabetical Order*

Balance, offset, 1 = T
Balance, offset, 2 = T*
Bias adjust = B
Blank position, without lead = X
Case = C
Compensation, input, 1 = F
Compensation, input, 2 = F*
Compensation, output, 1 = φ
Compensation, output, 2 = φ*
DC supply, +ve = V+
DC supply, -ve = V-
Frequency compensation, input, 1 = F
Frequency compensation, input, 2 = F*
Frequency compensation, output, 1 = φ
Frequency compensation, output, 2 = φ*
Gain adjust, 1 = A
Gain adjust, 2 = A*
Ground = G
Guard ring = W
Input, inverting, high-level = J-
Input, non-inverting, high-level = J+
Input, inverting, low-level = E-
Input, non-inverting, low-level = E+
Input offset voltage, adjust, 1 = T
Input offset voltage, adjust, 2 = T*
Lead omitted, blank position = X
Lead in position but not connected = N
Metal case = M
Not connected, but lead in position = N
Null, offset, 1 = T
Null, offset, 2 = T*
Offset voltage adjust, 1 = T
Offset voltage adjust, 2 = T*
Output, 1 = R
Output, 2 = R*
Output, open-collector = K
Output, open-emitter = L
Package = C
Special purpose terminal (data sheet to be consulted) = Q
Strobe = S
Supply, dc, +ve = V+
Supply, dc, -ve = V-
Supply, dc, supplementary, +ve = ++
Supply, dc, supplementary, -ve = --
Trim (offset voltage), 1 = T
Trim (offset voltage), 2 = T*

Appendix F



Appendix F

