

| | | | | | | |
|-------------|----------|---|-----|----------------|--------|---|
| 2 N 3821 | N-FET | Uni/VHF, 50V, Idss>0,5mA, Up<4V | 5k | - | | |
| 2 N 3822 | N-FET | Uni/VHF, 50V, Idss>2mA, Up<6V | 5k | - | | |
| 2 N 3823 | N-FET | VHF, ra, 30V, Idss>4mA, Up<8V | 5k | BF 245 | 7f | |
| 2 N 3824 | N-FET | Chopper, sym, Idss>12mA | 5k | - | | |
| 2 N 3854 | Si-N | Uni, 18V, 0,1A, 0,2W, >100MHz, B>35 | 7c | BC 546 | 7a | |
| 2 N 3854 A | Si-N | =2N3854: 30V | 7c | BC 546 | 7a | |
| 2 N 3855 | Si-N | =2N3854: >130MHz, B>60 | 7c | BC 546 | 7a | |
| 2 N 3855 A | Si-N | =2N3855: 30V | 7c | BC 546 | 7a | |
| 2 N 3856 | Si-N | =2N3854: >140MHz, B>100 | 7c | BC 546 | 7a | |
| 2 N 3856 A | Si-N | =2N3856: 30V | 7c | BC 546 | 7a | |
| 2 N 3866(A) | Si-N | VHF/UHF-O/Tr, 55V, 0,4A, PQ>1W(400MHz) | 2a | - | | |
| 2 N 3877 | Si-N | Nix, 70V, 0,05A, 0,2W, 160MHz | 7c | BC 546,BF 420A | 7a, 7c | |
| 2 N 3877 A | Si-N | =2N3877: 85V | 7c | BC 546,BF 420A | 7a, 7c | |
| 2 N 3903 | Si-N | Uni, 60V, 0,2A, 0,625W, >250MHz, B>50 | 7e | BC 546 | 7a | |
| 2 N 3904 | Si-N | =2N3903: B>100 | 7e | BC 546 | 7a | |
| 2 N 3905 | Si-P | Uni, 40V, 0,2A, 0,625W, >200MHz, B>50 | 7e | BC 556 | 7a | |
| 2 N 3906 | Si-P | =2N3905: B>100 | 7e | BC 556 | 7a | |
| 2 N 3930 | Si-P | Vid, 180V, 0,05A, 0,4W, >40MHz | 2a | BF 421 A | 7c | |
| 2 N 3931 | Si-P | =2N3930: 0,7W | 2a | MPSU 60 | 13m | 6 |
| 2 N 4026 | Si-P | S, 60V, 1A, 0,5W, <100/400ns, B>40 | 2a | BC 640 | 7c | |
| 2 N 4027 | Si-P | =2N4026: 80V | 2a | BC 640 | 7c | |
| 2 N 4028 | Si-P | =2N4026: B>100 | 2a | BC 640 | 7c | |
| 2 N 4029 | Si-P | =2N4026: 80V, B>100 | 2a | BC 640 | 7c | |
| 2 N 4030 | Si-P | =2N4026: 0,8W | 2a | BC 161 | 2a | |
| 2 N 4031 | Si-P | =2N4027: 0,8W | 2a | (BC 161) | 2a | 6 |
| 2 N 4032 | Si-P | =2N4028: 0,8W | 2a | BC 161 | 2a | |
| 2 N 4033 | Si-P | =2N4029: 0,8W | 2a | (BC 161) | 2a | 6 |
| 2 N 4036 | Si-P | NF/S, 90V, 1A, 1W, <110/700ns | 2a | (BC 161) | 2a | 6 |
| 2 N 4037 | Si-P | NF/S, 60V, 1A, 1W, >60MHz | 2a | BC 161 | 2a | |
| 2 N 4058 | Si-P | NF-V, ra, 30V, 0,03A, 0,36W | 7c | BC 560 | 7a | |
| 2 N 4059 | Si-P | NF, 30V, 0,03A, 0,36W, B>45 | 7c | BC 560 | 7a | |
| 2 N 4061 | Si-P | =2N4060: B>90 | 7c | BC 560 | 7a | |
| 2 N 4062 | Si-P | =2N4060: B>180 | 7c | BC 560 | 7a | |
| 2 N 4091(A) | N-FET | S, Chopper, 40...50V, Idss>30mA, Up<10V | 2b | - | | |
| 2 N 4092(A) | N-FET | S, Chopper, 40...50V, Idss>15mA, Up<7V | 2b | - | | |
| 2 N 4093(A) | N-FET | S, Chopper, 40...50V, Idss>8mA, Up<5V | 2a | - | | |
| 2 N 4096 | 50Hz-Thy | 50V, 0,4A(Tc=85°), Igt/Ih<0,2/<2mA | 2b | BRX 49 | 7a | |
| 2 N 4097 | 50Hz-Thy | =2N4096: 100V | 2a | BRX 49 | 7a | |
| 2 N 4098 | 50Hz-Thy | =2N4096: 200V | 2a | BRX 49 | 7a | |
| 2 N 4101 | 50Hz-Thy | =2N3228: 600V | 22a | (TAG 626-600) | 17e | 5 |
| 2 N 4108 | 50Hz-Thy | =2N4096 | 2a | BRX 49 | 7a | |
| 2 N 4109 | 50Hz-Thy | =2N4096 | 2a | BRX 49 | 7a | |
| 2 N 4110 | 50Hz-Thy | =2N4096 | 2a | BRX 49 | 7a | |
| 2 N 4121 | Si-P | Uni, 40V, 0,1A, 0,2W, <45/180ns, B>70 | 8a | (BF 324) | 7a | |
| 2 N 4122 | Si-P | =2N4122: B>150 | 8a | (BF 324) | 7a | |
| 2 N 4123 | Si-N | NF/S, 40V, 0,2A, 0,625W, 37/136ns | 7e | BC 546 | 7a | |
| 2 N 4124 | Si-N | NF/S, 30V, 0,2A, 0,625W, 37/136ns | 7e | BC 546 | 7a | |
| 2 N 4125 | Si-P | NF/S, 30V, 0,2A, 0,625W, 43/155ns | 7e | BC 556 | 7a | |
| 2 N 4126 | Si-P | NF/S, 25V, 0,2A, 0,625W, 43/155ns | 7e | BC 556 | 7a | |
| 2 N 4212 | 50Hz-Thy | 25V, 1,6A, Igt/Ih<0,1/3mA | 2a | TAG 103 X | 2a | |
| 2 N 4213 | 50Hz-Thy | =2N4212: 50V | 2a | BRX 49 | 7a | |
| 2 N 4214 | 50Hz-Thy | =2N4212: 100V | 2a | BRX 49 | 7a | |
| 2 N 4215 | 50Hz-Thy | =2N4212: 150V | 2a | BRX 49 | 7a | |
| 2 N 4216 | 50Hz-Thy | =2N4212: 200V | 2a | BRX 49 | 7a | |
| 2 N 4217 | 50Hz-Thy | =2N4212: 250V | 2a | BRX 49 | 7a | |
| 2 N 4218 | 50Hz-Thy | =2N4212: 300V | 2a | BRX 49 | 7a | |