

| | | | | | | | | |
|----------|--------------|-----------|---|-------------|------------|------------------------|-----|--|
| BC 312 | Sgs | Si-N | LF, 100/100V, 0.15A, 0.8W | 2a | TO-39 | BC 141 | 2a | BC 141, BC 300, BF 257...259, ++ |
| BC 313 | Tho | Si-P | LF Drv,Out, 60/40V, 1A, 0.8W, 200MHz | (BC211) 2a | TO-39 | BC 161 | 2a | BC 161, BC 461, BCX 60, 2N4235...4236 |
| BC 313 A | | Si-P | =BC 211: 80/60V | 2a | TO-39 | (BC 161) ⁷ | 2a | BC 461, BCX 60, 2N4236 |
| BC 314 | Sgs | Si-N | Uni, 120/120V, 0.05A, 0.18W, >50MHz | 8a | TO-106 | 2SC2632 | 7c | BF 422, 2SC1890A, 2SC2240, 2631...32, ++ |
| BC 315 | Tix | Si-P | LF Imp In, 45/35V, 0.1A, 0.3W, >200MHz, F<2dB(1kHz) | 7a | SOT-30 | BC 560 | 7a | BC 212, BC 415...416, BC 560, 2SA1137, ++ |
| BC 317 | Fch, Mot, ++ | Si-N | =BC 318: 50/45V | (BC320) 7e | TO-92 | BC 546 | 7a | BC 167, BC 182, BC 237, BC 547, 2SD767++ |
| BC 318 | Fch, Mot, ++ | Si-N | Uni, 40/30V, 0.15/0.3A, 0.35W, 280MHz | (BC321) 7e | TO-92 | BC 546 | 7a | BC 167, BC 183, BC 237, BC 547, 2SD767++ |
| BC 319 | Fch, Mot, ++ | Si-N | =BC 318: 30/20V, In, F<4dB(1kHz) | (BC322) 7e | TO-92 | BC 550 | 7a | BC 169, BC 184, BC 239, BC 549, 2SC2675++ |
| BC 320 | Fch, Mot, ++ | Si-P | =BC 321: 50/45V | (BC317) 7e | TO-92 | BC 556 | 7a | BC 212, BC 257, BC 307, BC 557, 2SB725++ |
| BC 321 | Fch, Mot, ++ | Si-P | Uni, 45/30V, 0.15/0.3A, 0.31W, 250MHz | (BC318) 7e | TO-92 | BC 556 | 7a | BC 213, BC 257, BC 307, BC 557, 2SB725++ |
| BC 322 | Fch, Mot, | Si-P | =BC 321: 30/20V, In, F<4dB(1kHz) | (BC319) 7e | TO-92 | BC 560 | 7a | BC 214, BC 259, BC 309, BC 559, 2SA1137+ |
| BC 323 | Sgs | Si-N | TV-VA, 100/60V, 5A, 0.8W/7W(Tc=25°), 100MHz | 2a | TO-39 | (BD 189) ⁴ | 14h | BFT 33...34, BDX 35...37, 2N5339...5339 |
| BC 324 | Sgs | Si-N | TV-VA, 85/55V, 1A, 0.8W/4W(Tc=25°), 100MHz | 2a | TO-39 | BC 141 | 2a | BC 140...141, BCX 40, 2N3019...3020, ++ |
| BC 325 | Tix | Si-P | LF In, 60/60V, 50mA, 0.36W, hFE=40...120, F<4dB | 2a | TO-18 | BC 560 | 7a | BC 214, BC 415...416, BC 560, 2SA1137, ++ |
| BC 326 | Tix | Si-P | =BC 325: hFE=100...500, F<3dB(1kHz) | 2a | TO-18 | BC 560 | 7a | BC 214, BC 415...416, BC 560, 2SA1137, ++ |
| BC 327 | EUR | Si-P | LF Drv, 50/45V, 0.8/1A, 0.625W, 100MHz | (BC337) 7a | TO-92 | BC 327 | 7a | BC 638, BC 640, 2SB1116(A), 2SB1437, ++ |
| BC 327 A | Phi | Si-P | =BC 327: 60/60V | 7a | TO-92 | BC 640 | 7c | BC 638, BC 640, 2SB1116(A), 2SB1437, ++ |
| BC 327 L | Tix | Si-P | =BC 327: | 7c | TO-92 | -BC 327 | | -BC 327 |
| BC 327 P | Fer | Si-P | =BC 327: | 40e | =TO-92 | -BC 327 | | -BC 327 |
| BC 328 | EUR | Si-P | =BC 327: 30/25V | (BC338) 7a | TO-92 | BC 327 | 7a | BC 636, BC 638, 2SB909, 2SB1116(A), ++ |
| BC 328 L | Tix | Si-P | =BC 328: | 7c | TO-92 | -BC 328 | | -BC 328 |
| BC 328 P | Fer | Si-P | =BC 328: | 40e | =TO-92 | -BC 328 | | -BC 328 |
| BC 329 | Tix | Si-N | LF Imp In, 60/60V, 30mA, 0.25W, F<2dB(1kHz) | 7a | SOT-30 | BC 550 | 7a | BC 184, BC 413...414, BC 550, 2SC2675, ++ |
| BC 330 | Tix | Si-N | =BC 329: 45/45V | 7a | SOT-30 | BC 550 | 7a | BC 184, BC 413...414, BC 550, 2SC2675, ++ |
| BC 331 | Tix | Si-N | LF Imp In, 60/60V, 30mA, 0.25W, F<6dB(1kHz) | 7a | SOT-30 | BC 550 | 7a | BC 184, BC 413...414, BC 550, 2SC2675, ++ |
| BC 332 | Tix | Si-N | =BC 321: 45/45V | 7a | SOT-30 | BC 550 | 7a | BC 184, BC 413...414, BC 550, 2SC2675, ++ |
| BC 333 | Mot | Si-N | Uni, 25/25V, 50mA, 0.31W, 50MHz | (BC334) 7e | TO-92 | BC 546 | 7a | BC 168, BC 183, BC 238, BC 548, 2SD767++ |
| BC 334 | Mot | Si-P | Uni, 25/25V, 50mA, 0.31W, 50MHz | (BC333) 7e | TO-92 | BC 556 | 7a | BC 213, BC 258, BC 308, BC 558, 2SB725++ |
| BC 335 | Mot | Si-N | =BC 333: In, F<3dB(1kHz) | (BC336) 7e | TO-92 | BC 550 | 7a | BC 169, BC 184, BC 239, BC 549, 2SC2675++ |
| BC 336 | Mot | Si-P | =BC 334: In, F<3dB(1kHz) | (BC335) 7e | TO-92 | BC 560 | 7a | BC 214, BC 259, BC 309, BC 559, 2SA1137+ |
| BC 337 | EUR | Si-N | LF Drv, 50/45V, 0.8/1A, 0.625W, 100MHz | (BC327) 7a | TO-92 | BC 337 | 7a | BC 637, BC 639, 2SD1616(A), 2SD2181, ++ |
| BC 337 A | Phi | Si-N | =BC 337: 60/60V | 7a | TO-92 | BC 639 | 7c | BC 637, BC 639, 2SD1616(A), 2SD2181, ++ |
| BC 337 L | Tix | Si-N | =BC 337: | 7c | TO-92 | -BC 337 | | -BC 337 |
| BC 337 P | Fer | Si-N | =BC 337: | 40e | =TO-92 | -BC 337 | | -BC 337 |
| BC 338 | EUR | Si-N | =BC 337: 30/25V | (BC328) 7a | TO-92 | BC 337 | 7a | BC 635, BC 637, 2SD1225, 2SD1616(A), ++ |
| BC 338 L | Tix | Si-N | =BC 338: | 7c | TO-92 | -BC 338 | | -BC 338 |
| BC 338 P | Fer | Si-N | =BC 338: | 40e | =TO-92 | -BC 338 | | -BC 338 |
| BC 340 | Itt | Si-N | LF Drv,Out, 40/40V, 0.5A, 0.8W, 100MHz | (BC360) 2a | TO-39 | BC 141 | 2a | BC 140...141, BC 300...302, 2N1990, ++ |
| BC 341 | Itt | Si-N | =BC 340: 60/60V | (BC361) 2a | TO-39 | BC 141 | 2a | BC 140...141, BC 300...302, 2N1990, ++ |
| BC 342 | Mot | Si-N | LF Drv,Out, 70/60V, 1A, 0.8W, 100MHz | (BC343) 2a | TO-39 | BC 141 | 2a | BC 140...141, BCX 40, 2N3019...3020, ++ |
| BC 343 | Mot | Si-P | LF Drv,Out, 70/60V, 1A, 0.8W, 100MHz | (BC342) 2a | TO-39 | BC 161 | 2a | BC 161, BCX 60, 2N4236, ++ |
| BC 344 | Mot | Si-N | =BC 342: 90/80V | (BC345) 2a | TO-39 | BC 141 | 2a | BC 141, BCX 40, 2N3019...3020, ++ |
| BC 345 | Mot | Si-P | =BC 343: 90/80V | (BC344) 2a | TO-39 | BC 161 | 2a | BC 461, BCX 60 |
| BC 347 | Mot | Si-N | Uni, 50/45V, 0.1A, 0.3W, >125MHz | (BC350) 7e | TO-92 | BC 546 | 7a | BC 167, BC 182, BC 237, BC 547, 2SD767++ |
| BC 348 | Mot | Si-N | =BC 347: 40/30V | (BC351) 7e | TO-92 | BC 546 | 7a | BC 167, BC 183, BC 237, BC 547, 2SD767++ |
| BC 349 | Mot | Si-N | =BC 347: 30/20V | (BC352) 7e | TO-92 | BC 546 | 7a | BC 168, BC 183, BC 238, BC 548, 2SD767++ |
| BC 350 | Mot | Si-P | Uni, 50/45V, 0.1A, 0.3W, >125MHz | (BC347) 7e | TO-92 | BC 556 | 7a | BC 212, BC 257, BC 307, BC 557, 2SB725++ |
| BC 351 | Mot | Si-P | =BC 350: 40/30V | (BC348) 7e | TO-92 | BC 556 | 7a | BC 213, BC 257, BC 307, BC 557, 2SB725++ |
| BC 352 | Mot | Si-P | =BC 350: 30/20V | (BC349) 7e | TO-92 | BC 556 | 7a | BC 213, BC 258, BC 308, BC 558, 2SB725++ |
| BC 354 | Mot | Si-P | Uni, 30/25V, 0.2A, 0.31W, >200MHz | 7e | TO-92 | BC 556 | 7a | BC 213, BC 258, BC 308, BC 558, 2SB725++ |
| BC 355 | Mot | Si-P | Uni, 30/25V, 0.2A, 0.31W, >200MHz | 7e | TO-92 | BC 556 | 7a | BC 213, BC 258, BC 308, BC 558, 2SB725++ |
| BC 357 | Mot | Si-P | Uni, 25/25V, 0.1A, 0.31W, >125MHz | (BC358) 7e | TO-92 | BC 556 | 7a | BC 213, BC 258, BC 308, BC 558, 2SB725++ |
| BC 358 | Mot | Si-N | Uni, 25/25V, 0.1A, 0.31W, >125MHz | (BC357) 7e | TO-92 | BC 546 | 7a | BC 168, BC 183, BC 238, BC 548, 2SD767++ |
| BC 360 | Itt | Si-P | LF Drv,Out, 40/40V, 0.5A, 0.8W, 250MHz | (BC340) 2a | TO-39 | BC 161 | 2a | BC 160...161, BC 303...304, BCX 60, ++ |
| BC 361 | Itt | Si-P | =BC 360: 60/60V | (BC341) 2a | TO-39 | BC 161 | 2a | BC 161, BC 303...304, BCX 60, ++ |
| BC 362 | Mot | Si-P | LF P, 50/45V, 2A, 8W, 100MHz | (BC365) 13m | (Uni watt) | (2SA1593) ⁴ | 30j | BD 518, BD 526, (2SB838...839, 2SB1201++) ⁴ |
| BC 363 | Mot | Si-P | =BC 362: 60/60V | (BC366) 13m | (Uni watt) | (2SA1593) ⁴ | 30j | BD 518, BD 526, (2SB839, 2SB1201, ++) ⁴ |
| BC 364 | Mot | Si-P | =BC 362: 80/80V | (BC367) 13m | (Uni watt) | (2SA1593) ⁴ | 30j | BD 520, BD 528, (2SB839, 2SB957...958, ++) ⁴ |
| BC 365 | Mot | Si-N | LF P, 50/45V, 2A, 8W, 150MHz | (BC362) 13m | (Uni watt) | (2SC4135) ⁴ | 30j | BD 517, BD 525, (2SD1078...79, 2SD1801++) ⁴ |
| BC 366 | Mot | Si-N | =BC 365: 60/60V | (BC363) 13m | (Uni watt) | (2SC4135) ⁴ | 30j | BD 517, BD 525, (2SD1079, 2SD1801, ++) ⁴ |
| BC 367 | Mot | Si-N | =BC 365: 80/80V | (BC364) 13m | (Uni watt) | (2SC4135) ⁴ | 30j | BD 519, BD 527, (2SD1281...82, 2SD1801++) ⁴ |
| BC 368 | Phi, Sie, ++ | Si-N | LF Drv, 25/20V, 1/2A, 0.8W, 65MHz | (BC369) 7c | TO-92 | BC 639 | 7c | BC 337...338, BC 635, 2SD1225, 2SD1616, ++ |
| BC 369 | Phi, Sie, ++ | Si-P | LF Drv, 25/20V, 1/2A, 0.8W, 65MHz | (BC368) 7c | TO-92 | BC 640 | 7c | BC 327...328, BC 636, 2SB909, 2SB1116, ++ |
| BC 370 | Sgs | Si-P | LF Drv, 20/20V, 0.5/1A, 0.375W, 150MHz | 2a | TO-18 | BC 327 | 7a | BC 327...328, BC 636, 2SB909, 2SB1116, ++ |
| BC 371 | Sgs | Si-N | LF Drv,Out, 60V, 1A, 0.85W | 2a | TO-39 | BC 141 | 2a | BC 140...141, BCX 40, 2N3019...3020, ++ |
| BC 372 | Mot | Si-N-Darl | 100/100V, 1A, 0.625W, >100MHz, hFE>10000 | 7a | TO-92 | (BC 879) ¹³ | 7c | (BC 879, BSR 52, 2SD1660, 2SD2067, ++) ¹³ |
| BC 373 | Mot | Si-N-Darl | =BC 372: 80/80V | 7a | TO-92 | (BC 879) ¹³ | 7c | (BC 877, BC 879, BSR 51...52, 2SD1853, ++) ¹³ |
| BC 375 | Phi | Si-N | LF Drv,Out, 30/30V, 1/1.5A, 0.625W, 150MHz | (BC376) 7a | TO-92 | BC 337 | 7a | BC 337...338, BC 635, 2SD1225, 2SD1616, ++ |
| BC 376 | Phi | Si-P | LF Drv,Out, 30/30V, 1/1.5A, 0.625W, 100MHz | (BC375) 7a | TO-92 | BC 327 | 7a | BC 327...328, BC 636, 2SB909, 2SB1116, ++ |
| BC 377 | Sgs | Si-N | LF Drv, 50/45V, 1A, 0.375W, 200MHz | (BC297) 2a | TO-18 | BC 337 | 7a | BC337, BC637, BC639, 2SC4485, 2SD1616, ++ |
| BC 378 | Sgs | Si-N | =BC 377: 30/25V | (BC298) 2a | TO-18 | BC 337 | 7a | BC 337...338, BC 635, 2SC4485, 2SD1225, ++ |
| BC 381 | Tix | Si-P | Uni, 40/25V, 0.2A, 0.625W | 7a | SOT-30 | BC 327 | 7a | BC 327, BC 636, BC 638, 2SA1515, ++ |
| BC 382 | Tix | Si-N | LF In, 50/45V, 0.1A, 0.3W, >150MHz | 7a | SOT-30 | BC 550 | 7a | BC 184, BC 413...414, BC 550, 2SC2675, ++ |
| BC 383 | Tix | Si-N | =BC 382: 45/30V | 7a | SOT-30 | BC 550 | 7a | BC 184, BC 413...414, BC 550, 2SC2675, ++ |
| BC 384 | Tix | Si-N | =BC 382: 45/30V, Ur<0, 135µV | 7a | SOT-30 | BC 550 | 7a | BC 184, BC 413...414, BC 550, 2SC2675, ++ |
| BC 385 | Tix | Si-N | Uni, 45/45V, 0.1/0.2A, 0.3W, >150MHz | 7a | SOT-30 | BC 546 | 7a | BC 167, BC 183, BC 237, BC 547, 2SD767++ |
| BC 386 | Tix | Si-N | Uni, 45V, 0.1A, 0.3W, >150MHz | 7a | SOT-30 | BC 546 | 7a | BC 167, BC 183, BC 237, BC 547, 2SD767++ |
| BC 387 | Mot | Si-N | LF Drv, 35/30V, 0.6A, 0.31W | (BC388) 7e | TO-92 | BC 337 | 7a | BC337, BC635, BC637, 2SC4485, 2SD1225, ++ |
| BC 388 | Mot | Si-P | LF Drv, 35/30V, 0.6A, 0.31W | (BC387) 7e | TO-92 | BC 327 | 7a | BC 327, BC 536, BC 638, 2SA1705, 2SB909, ++ |
| BC 389 | Sgs | Si-N | Uni, -/45V, 0.2A, 0.3W, >150MHz, hFE>40 | 2a | TO-18 | BC 546 | 7a | BC 167, BC 183, BC 237, BC 547, 2SD767++ |
| BC 390 | Sgs | Si-N | =BC 389: -/20V | 2a | TO-18 | BC 546 | 7a | BC 168, BC 183, BC 238, BC 548, 2SD767++ |
| BC 391 | Sgs | Si-N | =BC 389: -/20V, hFE>100 | 2a | TO-18 | BC 546 | 7a | BC 168, BC 183, BC 238, BC 548, 2SD767++ |
| BC 393 | Mot, Sgs | Si-P | LF Vid, 180/180V, 0.1A, 0.4W, 120MHz | (BC394) 2a | TO-18 | BF 421 A | 7c | BF 423, BF436...37, BF 491...93, 2SB1349, ++ |
| BC 394 | Mot, Sgs | Si-N | LF Vid, 180/180V, 0.1A, 0.4W, 90MHz | (BC393) 2a | TO-18 | BF 420 A | 7c | BF 298...99, BF 391...93, BF 423, 2SD2031, ++ |
| BC 395 | Sgs | Si-N | TV-VA Drv, 80/70V, 0.5A, 0.3W, >60MHz | (BC396) 8a | TO-105 | BC 141 | 2a | BC 140...41, BC 300...01, BC 639, 2SD2181+ |
| BC 396 | Sgs | Si-P | TV-VA Drv, 80/70V, 0.5A, 0.3W | (BC395) 8a | TO-105 | BC 161 | 2a | BC 303, BC 640, 2SA1708, 2SB1437, ++ |
| BC 397 | Sgs | Si-P | LF Drv,Out, 50/40V, 1A, 0.8W | 2a | TO-5 | BC 161 | 2a | BC 161, BC 460...461, BCX 60, ++ |
| BC 398 | Sgs | Si-N | LF Drv,Out, 60/50V, 1A, 0.8W | 2a | TO-5 | BC 141 | 2a | BC 140...141, BC 440...441, BCX 40, ++ |
| BC 399 | Sgs | Si-N | Min, LF In, 30/20V, 75mA, 75mW | 36a | (2x1,8mm) | (BC 550) ⁶ | 7a | BC 122...123 |
| BC 400 | Sgs | Si-P | Uni, 90/80V, 50mA, 0.2W, 150MHz | 8a | TO-106 | BC 556 | 7a | BC 477, 2SA893(A), 2SA1017, SB715, ++ |
| BC 404 | Sgs | Si-P | Uni, 80/60V, 0.15A, 0.36W, 150MHz | 7a | TO-92 | BC 556 | 7a | BC 477, BC 556, 2SA1136...37, 2SA1335, ++ |
| BC 405 | Sgs | Si-P | =BC 404: 60/60V, In, F<4dB(1kHz) | 7a | TO-92 | BC 560 | 7a | BC 416, BC 560, 2SA1136...1137, 2SA1335, ++ |
| BC 406 | Sgs | Si-P | =BC 404: 40/40V, In, F<2dB(1kHz) | 7a | TO-92 | BC 560 | 7a | BC 214, BC 415...416, BC 560, 2SA1136...37, ++ |