

BDX 96	Si-P	=BDX 92: 100V	23a	BD 318	23a
--------	------	---------------	-----	--------	-----

## BDY

BDY 17	Si-N	NF/S-L, 80V, 10A, 115W, 1MHz	23a	2SD1047	18j
BDY 18	Si-N	=BDY 17: 120V	23a	2SD1047	18j
BDY 19	Si-N	=BDY 17: 150V	23a	2SD1047	18j
BDY 20	Si-N	NF/S-L, 100V, 15A, 117W, 1MHz	23a	2N3055	23a
BDY 25	Si-N	=BDY 23: 200V	23a	MJ 15015	23a
BDY 34	Si-N	NF/S-L, 45V, 3A, 21W, >80MHz	14h	2SD1348	14h
BDY 37	Si-N	NF/S-L, 160V, 16A, 150W, >0,2MHz	23a	MJ 15015	23a
BDY 37 A	Si-N	=BDY 37: 250W	23a	-	
BDY 38	Si-N	NF/S-L, 50V, 6A, 117W, 1MHz	23a	2N3055	23a
BDY 39	Si-N	NF/S-L, 100V, 15A, 117W, 1.1MHz	23a	2N3055	23a
BDY 55	Si-N	NF/S-L, 100V, 15A, 115W, >10MHz	23a	2N3055	23a
BDY 56	Si-N	=BDY 55: 180V	23a	MJ 15015	23a
BDY 77	Si-N	=BDY 75: 150V, 16A	23a	MJ 15015	23a
BDY 80	Si-N	NF/S-L, 40V, 4A, 36W, 3MHz	17j	BD 243 C	17j
BDY 81	Si-N	=BDY 80: 60V	17j	BD 243 C	17j
BDY 82	Si-P	NF/S-L, 35V, 4A, 36W, 3MHz	17j	BD 244 C	17j
BDY 83	Si-P	=BDY 82: 50V	17j	BD 244 C	17j

## BF

BF 108	Si-N	Vid, 140V, 0,15A, 0,86W, 180MHz	2a	BF 259	2a
BF 109	Si-N	Vid, 135V, 0,05A, 0,52W, >80MHz	2a	BF 259	2a
BF 110	Si-N	Vid, 160V, 0,04A, 0,75W, 150MHz	2a	BF 259	2a
BF 111	Si-N	Vid, 200V, 0,08A, 0,8W, 120MHz	2a	BF 259	2a
BF 114	Si-N	Vid, 135V, 0,04A, 1,2W(Tc=60°), >80MHz	2a	BF 259	2a
BF 115	Si-N	AM/FM-V/M/O/ZF, 230MHz	5k	BF 255	7d
BF 117	Si-N	Vid, 140V, 0,1A, 0,68W, 80MHz	2a	BF 259	2a
BF 118	Si-N	Vid, 250V, 0,1A, 0,8W, 110MHz	2a	BF 259	2a
BF 119	Si-N	Vid, 160V, 0,1A, 0,8W, 110MHz	2a	BF 259	2a
BF 120	Si-N	Vid, TV-HA-O, 220V, 0,05A, 0,3W	2a	BF 420 A	7c
BF 121	Si-N	AM/FM-V-re, 350MHz	6k	BF 198	7d
BF 123	Si-N	TV-ZF, 550MHz	6k	BF 199	7d
BF 125	Si-N	AM/FM-M/O/ZF, 450MHz	6k	BF 199	7d
BF 127	Si-N	TV-ZF-re, 350MHz	6k	BF 198	7d
BF 130	Si-N	Uni, 45V, 0,1A, 150MHz	8a	BC 546	7a
BF 131	Si-N	=BF 130:	2a	BC 546	7a
BF 132	Si-N	Uni, 25V, 0,1A, 270MHz	2a	BC 546	7a
BF 133	Si-N	=BF 132:	8a	BC 546	7a
BF 134	Si-N	FM-M/O, >600MHz	8a	BF 255	7d
BF 136	Si-N	FM-V-re, 600MHz	8a	BF 255	7d
BF 137	Si-N	Vid, 160V, 0,1A, 0,68W, 95MHz	2a	BF 259	2a
BF 138	Si-N	FM-V-re, 600MHz	8a	BF 198	7d
BF 140	Si-N	Vid, 135V, 0,05A, 0,8W, 100MHz	2a	BF 259	2a
BF 140 A	Si-N	=BF 140: 150V	2a	BF 259	2a
BF 140 D	Si-N	=BF 140: 180V	2a	BF 259	2a
BF 140 R	Si-N	=BF 140: 0,03A, 0,3W	2a	BF 420 A	7c
BF 140 S	Si-N	=BF 140: 0,03A	2a	BF 259	2a
BF 152	Si-N	VHF-M/O, 800MHz	8a	BF 199	7d
BF 153	Si-N	AM-ZF, 400MHz	8a	BF 199, BF 255	7d
BF 154	Si-N	Vid-Tr, 30V, 0,05A, 0,3W, 400MHz	8a	BF 959	7d
BF 155	Si-N	UHF-V/M/O, 600MHz	5g	2SC2570A	7f
BF 155 R	Si-N	Vid, 155V, 0,05A, 0,3W, >40MHz	2a	BF 420 A	7c