

BCW 18	Si-N	=BCW 10: 70V	40e	BC 639	7c
BCW 19	Si-P	=BCW 11: 70V	40e	BC 640	7c
BCW 20	Si-N	NF, ra, 30V, 0,3W, >30MHz	40e	BC 550	7a
BCW 21	Si-P	NF, ra, 30V, 0,3W, >30MHz	40e	BC 560	7a
BCW 22	Si-N	=BCW 20: 45V	40e	BC 550	7a
BCW 23	Si-P	=BCW 20: 45V	40e	BC 560	7a
BCW 24	Si-N	NF, ra, 45V, 30mA, 0,3W, >30MHz	2a	BC 550	7a
BCW 29	Si-P	SMD, Uni, 30V, 0,1A, 150MHz, B=>120	35a	BC 856	35a
BCW 29 R	Si-P	=BCW 29:	35d	-	
BCW 30	Si-P	=BCW 29: B>215	35a	BC 856	35a
BCW 30 R	Si-P	=BCW 30:	35d	-	
BCW 31	Si-N	SMD, Uni, 30V, 0,1A, 300MHz, B>110	35a	BC 846	35a
BCW 31 R	Si-N	=BCW 31:	35d	-	
BCW 32	Si-N	=BCW 31: B>200	35a	BC 846	35a
BCW 32 R	Si-N	=BCW 32:	35d	-	
BCW 33	Si-N	=BCW 31: B>420	35a	BC 846	35a
BCW 33 R	Si-N	=BCW 33:	35d	-	
BCW 46	Si-N	=BCW 48: 80V	12a	BC 546	7a
BCW 47	Si-N	=BCW 48: 50V	12a	BC 546	7a
BCW 48	Si-N	Uni, 30V, 0,1A, 0,2W, 300MHz	12a	BC 546	7a
BCW 49	Si-N	=BCW 48: ra	12a	BC 550	7a
BCW 50	Si-N	NF, 120V, 0,5W, >50MHz	2a	2SC2632	7c(9mm)
BCW 56	Si-P	=BCW 58: 80V	12a	BC 556	7a
BCW 57	Si-P	=BCW 58: 50V	12a	BC 556	7a
BCW 58	Si-P	Uni, 30V, 0,1A, 0,2W, 150MHz	12a	BC 556	7a
BCW 59	Si-P	=BCW 58: ra	12a	BC 560	7a
BCW 60	Si-N	SMD, Uni, 32V, 0,2A, 250MHz	35a	BC 846	35a
BCW 60 R	Si-N	=BCW 60:	35d	-	
BCW 61	Si-P	SMD, Uni, 32V, 0,2A, 180MHz	35a	BC 856	35a
BCW 61 R	Si-P	=BCW 61:	35d	-	
BCW 65	Si-N	SMD, NF/S, 60V, 0,8A, >100MHz	35a	-	
BCW 65 R	Si-N	=BCW 65:	35d	-	
BCW 66	Si-N	=BCW 65: 75V	35a	-	
BCW 66 R	Si-N	=BCW 66:	35d	-	
BCW 67	Si-P	SMD, NF/S, 45V, 0,8A, >100MHz	35a	-	
BCW 67 R	Si-P	=BCW 67:	35d	-	
BCW 68	Si-P	=BCW 67: 60V	35a	-	
BCW 68 R	Si-P	=BCW 68:	35d	-	
BCW 69	Si-P	SMD, Uni, 50V, 0,1A, 150MHz, B>120	35a	BC 856	35a
BCW 69 R	Si-P	=BCW 69:	35d	-	
BCW 70	Si-P	=BCW 69: B>215	35a	BC 856	35a
BCW 70 R	Si-P	=BCW 70:	35d	-	
BCW 71	Si-N	SMD, NF, 50V, 0,1A, 300MHz, B>110	35a	BC 846	35a
BCW 71 R	Si-N	=BCW 71:	35d	-	
BCW 72	Si-N	=BCW 71: B>200	35a	BC 846	35a
BCW 72 R	Si-N	=BCW 72:	35d	-	
BCW 81	Si-N	=BCW 71: B>420	35a	BC 846	35a
BCW 81 R	Si-N	=BCW 81:	35d	-	
BCW 89	Si-P	=BCW 69: 80V	35a	BC 856	35a
BCW 89 R	Si-P	=BCW 89:	35d	-	
BCX 12	Si-N	NF/S, 125V, 0,8A, 0,625W, 100MHz	7a	2SD1812	7c
BCX 13	Si-P	NF/S, 125V, 0,8A, 0,625W, 120MHz	7a	2SB1212	7c
BCX 17	Si-P	SMD, NF-Tr, 50V, 0,5A, 100MHz	35a	BC 807	35a
BCX 17 R	Si-P	=BCX 17:	35d	-	
BCX 18	Si-P	=BCX 17: 30V	35a	BC 807	35a